

RESTORATION HARDWARE

HARBOR PENDANT

PARTS ENCLOSED HARDWARE INCLUDED

- | | |
|-----------------------|--------------------------------|
| (A) Mounting plate(1) | (a) Green ground screw (1) |
| (B) Canopy (1) | (b) Plastic wire connectors(2) |
| (C) Loop 1 (1) | (c) Plate screws(2) |
| (D) Loop 2 (1) | (d) Mounting screws (2) |
| (E) Chain links (2) | (e) Bulb (1) |

IMPORTANT SAFETY INSTRUCTIONS

WE RECOMMEND INSTALLATION BY A LICENSED ELECTRICIAN

This fixture has been rated for up to (1) 60-watt maximum TYPE B bulb. To avoid the risk of fire, do not exceed the recommended wattage.

WARNINGS

All wires are connected. When unpacking, be careful not to pull wires as a bad connection may result. Do not connect electricity until your lamp is fully assembled.

To reduce the risk of fire, electrical shock, or personal injury , always turn off lamp and allow it to cool prior to replacing light bulb.

Do not touch bulb when fixture is turned on or look directly at lit bulb. Keep flammable materials away from lit bulb.

This lighting fixture contains lead, a chemical know to the State of California to cause cancer,birth defects and other reproductive harm.Wash hands after installing, handling, cleaning or otherwise touching this light fixture.

TO ASSEMBLE

- Carefully remove all parts from the box and remove all plastic covering.
- Turn OFF power to the junction box where the lamp will be installed.
- Connect the loop 2(D) and the lower Chain link(E). Connect the loop 1(C) and the upper Chain link(E).
- Wrap the fixture's bare ground wire around green ground screw(a),and then fix the green ground screw into the mounting plate(A).
- Connect the hot wire hot the hot junction box wire (usually black) with a plastic wire connector (b) and wrap the connection with electrical tape. Connect the neutral wire to the neutral junction box wire(usually white) with a plastic wire connector(b) and wrap the connection with electrical tape.
- Attach the mounting plate(A) to the outlet box using the mounting screws(d).Tighten with a screwdriver.
- Attach the canopy(B) to the mounting plate(A) using the plate screws(c). Tighten screws with a screwdriver.
- Insert a 60-watt Type B bulb into threaded socket.
- Attach the cage by aligning the white circular dot with locking point A. Tighten the cage by twisting it counter-clockwise. To replace the bulb, loosen the cage by twisting it clockwise and replace the old bulb with a new one.
- Restore power to the junction box and test lamp fixture.
- Installation is complete.

CARE INSTRUCTIONS

Do not use polishes or cleaners on your lamp.
JUST WIPE CLEAN WITH SOFT CLOTH.

