

RESTORATION HARDWARE

ARC FLOOR LAMP

PARTS ENCLOSED:

- | | |
|---------------------|------------------------|
| (A) Base | (L) Column |
| (B) Base Holes (X2) | (M) Hole |
| (C) Wrench | (N) Screw |
| (D) Plate | (O) Loop |
| (E) Column | (P) Shade Washer |
| (F) Loader | (Q) Split Washer |
| (G) Washers (X2) | (R) Shade |
| (H) Bolts (X2) | (S) Polarized Plug |
| (I) Hole | (T) Protective Plastic |
| (J) Screw | (U) Foot Switch |
| (K) Column | |

IMPORTANT SAFETY INSTRUCTIONS:

1. These instructions are provided for your safety. It is very important that they are read carefully and completely before beginning the assembly and installation of this lighting fixture.
2. This lamp is equipped with a polarized plug (one blade is wider than the other). If the plug does not fit securely into the outlet, do not force it - contact a professional electrician. Use the plug with an extension cord only if it can be fully inserted into the cord's socket. Never alter the plug in any way.
3. This fixture has been rated for up to two (2) 100-watt maximum TYPE A, medium base light bulbs. To avoid the risk of fire, do not exceed the recommended wattage.

WARNINGS:

1. To reduce the risk of fire, electrical shock or personal injury, always turn off light fixture and allow it to cool prior to replacing light bulb.
2. Do not touch bulb when fixture is turned on. Do not look directly at lit bulb.
3. Keep flammable materials away from lit bulb.

TO ASSEMBLE:

NOTE: It is recommended that two people assemble the lamp per the following instructions to avoid injury or damage to the lamp.

1. Remove all parts from carton. Remove protective plastic and discard.
2. Remove bolts (H), washers (G), and plate (D) from the bottom of column (E). Set all parts aside.
3. Place base (A) on top of loader (F). Place both items on a level surface. Place plate (D) on top of base (A).
4. Set column (E) on top of plate (D). Threaded holes in the bottom of column (E) should align with holes (B).
5. Hold column (E), plate (D), base (A) and loader (F) together and carefully tilt parts to the side as shown in Illustration 1.
6. Slip washers (G) over bolts (H). Insert bolts (H) through holes in loader (F), base (A) and plate (D) as shown in Illustration 1. Bolts (H) will thread into the bottom of column (E). Use wrench (C) to tighten bolts (H).
7. Gently turn assembled base and column back into upright position. Make sure column (E) is securely attached to base (A). If column (E) seems loose, turn base over and tighten bolts (H) again.
8. Locate column (K) and remove screw (J) and set aside. Insert column (K) into column (E) as shown in Illustration 2. Insert screw (J) into hole (I) on column (E) to secure parts together. NOTE: The electrical cord on this lamp exits column (E) just above base (A). Pull the electrical cord exiting the column taut when inserting column (K) into column (E) to prevent damage to the wire.
9. Locate column (L) and remove screw (N) and set aside. Insert column (L) into column (K) as shown in Illustration 3. Insert screw (N) into hole (M) on column (K) to secure parts together. NOTE: The electrical cord on this lamp exits column (E) just above base (A). Pull the electrical cord exiting the column (E) taut when inserting column (L) into column (K) to prevent damage to the wire.
10. Lift shade (R) over socket cluster. Slide split washer (Q) between shade washer (P) and loop (O). Lift shade (R) so the top of shade washer (Q) is touching the bottom of loop (O). Secure position of shade (R) by turning shade washer (P) until it rests against the bottom of split washer (Q).
11. Install two (2) 100W MAX Type A, medium base bulbs into sockets.
12. Remove protective plastic (T) from polarized plug (S). Insert polarized plug into electrical outlet.
13. Use on-off foot switch (U) to control power to the lamp.

CARE INSTRUCTIONS:

1. Wipe clean with a soft, dry cloth or static duster.
2. Always avoid the use of harsh chemicals or abrasive cleaners as they may cause damage to the fixture's finish.

